

NEW

MIXER-PREAMPLIFIERS

AM-40D
AM-80D

40 W 80 W 100 V 4 - 16Ω DC 24V AUDIO CUTOFF

BLUETOOTH FM TUNER USB SD



DESCRIPTION

These mixer-amplifiers are available in 40W and 80W versions.

Multimedia player: FM Tuner / USB / SD / Bluetooth

They offer both 100V high-impedance speaker outputs and low-impedance outputs (4-16 Ω).

They operate on AC 240V – 50 Hz

DESCRIPTION

- They are equipped with :
- 1 combo input XLR / JACK 6.35 mm
 - 2 AUX RCA inputs
 - 1 LINE OUT RCA output
 - FM Tuner and MP3 / USB / SD player module
 - MBluetooth receiver module for streaming from smartphone, tablet or laptop
 - Thermal, overload, and short-circuit protection
 - Remote control included



SPECIFICATIONS	AM-40D	AM-80D
Type	Mixer-Preamplifier	
Power Supply	AC 240V – 50 Hz	
Output Power	40 W RMS	80 W RMS
Speaker Outputs	4-16 Ω / 100 V	
Output / Sensitivity	0 dBV / 600 Ω	
Inputs / Sensitivity	AUX 1-2: 400 mV / 550 mV MIC 1: 4 mV	
Tone Controls	Bass : ± 10 dB à 100 Hz Treble : ± 10 dB à 10 kHz	
Frequency Range	80 Hz - 20 000 Hz (± 3 dB)	
Signal-to-Noise Ratio	≥ 75 dB	
Total Harmonic Distortion	< 0,5 %	
Displays	Power indicator Output level VU-meters	
Dimensions (W x D x H)	220 x 230 x 66 mm - 2U	
Weight	4 kg	5 kg

MODEL DESIGNATIONS

- Mixer-Preamplifier 40 W **AM-40D**
(code 02787)
- Mixer-Preamplifier 80 W **AM-80D**
(code 02788)