

NEW

MICROPHONES SANS FIL

BE-1080

FRÉQUENCES
FIXES

8 CANAUX

RACKABLE



brackets included

DESCRIPTION

Professional-quality UHF set !

Equipped with a receiver

- UHF receiver equipped with receiver modules on 2 sets of fixed frequencies (8 channels)
- PLL automatic reception system
- Anti-interference system for simultaneous operation of several sets
- Reception distance of 50 metres
- Functions displayed on LCD screen
- Infrared 'sync' function for transmitting the frequency to the transmitters
- Ideal for vocal, singing or professional audio applications on stage
- 1 jack lead (mix output)
- Transmitter power: 10 mW
- FM modulation type
- Deviation: 22 KHz
- Information displayed on LCD screen
- Battery voltage: 3V (2 x 1.5V AA Battery)
- Continuous operating time: 5 hours

FREQUENCIES

There are 2 sets available with 8 fixed frequencies:

- 520.1 MHz - 527.7 MHz - 506.0 MHz - 517.5 MHz - 553.7 MHz - 557.7 MHz - 523.0 MHz - 546.5 MHz
- 607.1 MHz - 613.2 MHz - 655.0 MHz - 663.0 MHz - 644.1 MHz - 628.8 MHz - 670.4 MHz - 687.1 MHz

SPECIFICATIONS

BE-1080

Reception method	8-channel UHF receiver
System	Synthesised PLL
Frequency stability	< + 10 ppm
Interfering image rate	> 50 dB
Signal-to-noise ratio	> 70 dB
Sensitivity	- 80 dBuV
Total harmonic distortion	< 0,5 %
Bandwidth	80 Hz - 15 000 Hz (± 3 dB)
Output impedance	600 Ω
Audio output level	400 mV, balanced/unbalanced
Display	LCD
Audio output sockets	8 XLR balanced, 1 unbalanced jack
Antenna socket	4 x BNC
Power supply	DC 12V - 1000 ma
Consumption	< 5 W
Dimensions (W x D x H)	480 x 180 x 46 mm / rackable : brackets included
Weight (receiver + microphone)	2,75 Kg
Handheld microphone	BE-1080MIC
Batteries	2 x AA / 1.5 V (supplied)

MODEL DESIGNATIONS

8-microphone receiver set **BE-1080**
(code 02816)