

NEW

ÁN PLÍGÍĚŘ "PŘEÁN PLÍGÍĚŘ


SERIE AME-4Z

120 W
240 W
360 W

100 V
8 Ω

TUNER
FM

MP3
USB
SD



BLUETOOTH

DC24V

COUPURE
SONO
DC24V



AMPLIFIERS
PREAMPLIFIERS

DESCRIPTION

These mixer-amplifiers are available in 3 power ratings: 120W, 240W and 360W.
4 selectable zones
Standard operation in 100V (per zone or direct) and 8 Ω (direct only).
They operate on 220/240V - 50 Hz mains or DC 24V.

FEATURES

- They are equipped with :
- AM/FM tuner and USB/SD/Bluetooth player (antenna)
 - 3 balanced XLR combo MIC inputs, including 2 switchable 15 V phantom power supplies
 - 1 Alarm/In input on DC 24V contact
 - 1 Tel input with volume
 - 2 Chime and Fire inputs with priority on all sources (AUX/ MIC)
 - Mic 1 input with talk-over priority on all sources
 - 2 RCA LINE inputs
 - 1 RCA output
 - 1 individual volume control per input, 1 master volume control
 - Thermal, overload and short-circuit protection
 - Priority function (PA mute) on DC 24V terminal block
 - Siren triggered by on/off button on front panel
 - Supplied with 19" mounting brackets
 - Bluetooth pairing: "SEGON"

FEATURES

| FEATURES | AME-120-4Z | AME-240-4Z | AME-360-4Z |
|---------------------------|--|------------|------------|
| Type | Mixer amplifier with tuner/MP3/USB/SD/BLUETOOTH | | |
| Power supply | AC 220V/240 V – 50 Hz - DC 24V | | |
| Output power | 120 W RMS | 240 W RMS | 360 W RMS |
| Speaker outputs | 8 Ω / 100V | | |
| Frequency bands | 50 Hz - 19 000 Hz (± 3 dB) | | |
| Total harmonic distortion | < 1 % | | |
| Signal-to-noise ratio | MIC : > 80 dB LINE : > 85 dB | | |
| Tone Settings | Bass : +10dB à 100 Hz Treble : +10 dB à 10 000 Hz | | |
| Cooling | Fan | | |
| Consumption | 280 W | 460 W | 900 W |
| Phantom power | + 24 V switchable | | |
| Protection | Thermal, overload and short-circuit protection | | |
| Dimensions (W x D x H) | 420x330x88 | | 420x380x88 |
| Weight | 9 kg | 11 kg | 13kg |

MODEL DESIGNATIONS

- Mixing amplifier 120 W - 4 Zones **AME-120-4Z**
(code 02682)
- Mixing amplifier 240 W - 4 Zones **AME-240-4Z**
(code 02683)
- Mixing amplifier 360 W - 4 Zones **AME-360-4Z**
(code 02684)