

NEW

ĀN PLĪGĪEĒŠĀ PĒRĒĀN PLĪGĪEĒŠ

SERIE AME-2Z

60 W
120 W

100 V
8 Ω

TUNER
FM

MP3
MICRO SD
USB

BLUETOOTH

DC24V

SONO
CUT-OFF



AMPLIFIERS
PREAMPLIFIERS

DESCRIPTION

These mixer-amplifiers are available in 2 power ratings: 60W and 120W.

2 adjustable zones

Standard operation in 100V (per zone) and in 4-8-16 Ω and 70/100V (only direct).

They operate on 110/230V - 50/60 Hz mains or DC24V.

FEATURES

They are equipped with :

- AM/FM tuner and USB/SD/Bluetooth player
- 2 balanced MIC/LINE JACK 6.35 inputs
- 1 XLR MIC input
- 1 Tel input with priority volume on all sources (AUX/ MIC)
- 1 priority MIC XLR input
- 2 LINE RCA inputs
- 1 LINE RCA output + 1 MOH output on terminals
- 1 individual volume control per input, 1 master volume control
- Thermal, overload and short-circuit protection
- Priority function (sound cut-off) on one terminal block
- Siren triggered by on/off button on front panel
- Bluetooth pairing: "BT6678" mdp: 1234
- Remote control

FEATURES

	AME-60-2Z	AME-120-2Z
Type	Mixer amps with tuner/MP3/USB/SD/BLUETOOTH	
Power supply	AC 110V/230 V - 50/60 Hz - DC 24V	
Output power	60 W RMS	120 W RMS
Speaker outputs	4-8-16 Ω / 70 - 100V	
Frequency bands	60 Hz - 15 000 Hz (± 3 dB)	
Total harmonic distortion	< 0.5%	
Signal-to-noise ratio	MIC : > 72 dB LINE : > 85 dB	
Tone Settings	Bass : +10dB à 100 Hz Treble : +10 dB à 10 000 Hz	
Cooling	Fan	
Consumption	100 W	200W
Phantom power	+ DC24V switchable	
Protection	Thermal, overload and short-circuit protection	
Dimensions (W x D x H)	320 x 210 x 90	
Weight	3.95 kg	4.60 kg

MODEL DESIGNATIONS

- Mixing amplifier 60 W - 2 Zones AME-60-2Z
(code 02739)
- Mixing amplifier 120 W - 2 Zones AME-120-2Z
(code 02740)

Segon
PROFESSIONAL AUDIO