

MIXING CONSOLE

LA-MIX4USB



DESCRIPTION

- Integrated USB sound card
- Integrated Bluetooth receiver
- Jack/XLR combo input with phantom power
- 1 stereo input channel with volume control
- 1 mono input channel with low mic noise - preamp 4-band equalizer and pan/balance for each channel

FEATURES

It is equipped with :

- 2 balanced MIC/LINE XLR inputs
- 2 mono XLR and 6.35 mm stereo inputs
- 1 stereo RCA and balanced 6.35 mm jack input
- 1 compressor input 1 and 2
- 48 V phantom power supply with ON/OFF switch on rear of console
- 4-band equalizer, PEAK LED on each MIC channel
- 1 Aux/Send per channel for external effects and monitoring
- Balanced jack outputs for control and headphones
- Digital display
- USB and Bluetooth multimedia player Bluetooth

FEATURES

LA-MIX4USB

Type	Mixing Console
Power Supply	5V AC or USB adapter.
parametric equalizer High	12KHz ± 15dB
parametric equalizer Low	80Hz/± 15dB
Inputs	3.5 + 6.3mm Jack, RCA, XLR
Outputs	3.5mm Jack, RCA
Frequency response:	20Hz ~ 20KHz/± 0.5dB
Sensitivity range	+20 à -20 dB
Signal-to-noise ratio	> 90 dB
Total harmonic distortion	< 0,1 %
DSP mode	100 pre-recorded effects Hall, vocal, room... À / D and D / A converters: 24 bit
Dimensions (L x P x h)	150 x 180 x 50 mm
Weight	1,9kg

MODEL DESIGNATIONS

4-channel mixer	LA-MIX4USB (code 02706)
-----------------------	----------------------------

