

ĀN PLĪGĪĒRĀRĒĀN PLĪGĪĒR

MA-30 MA-60 MA-120

30 W
60 W
120 W

70 V
100 V
16 Ω

TUNER
FM

MP3
USB
SD



AMPLIFIERS
PREAMPLIFIERS

DESCRIPTION

These mixer-amplifiers are available in 3 power ratings: 30 W, 60 W and 120 W.

Standard operation 4 - 8 - 16 Ω (Low Impedance) 70V / 100V.

They operate on 220V - 50/60 Hz or DC 24V.

FEATURES

They are equipped with :

- AM/FM tuner and MP3/USB/Bluetooth player
- 1 balanced MIC/ XLR input with switchable 24V phantom power supply
- 2 switchable Mic/LINE 1 inputs with unbalanced jacks
- 2 LINE input: AUX
- 1 LINE Out /RCA output
- 1 Individual volume control for each input, 1 master volume control
- Thermal, overload and short-circuit protection
- Supplied with remote control
- Please note: Bluetooth pairing on the amplifier is done using the name "Ulysse" and the password: 1234.

MODEL DESIGNATIONS

30 W amplifier-mixer	MA-30 (code 02276)
60 W amplifier-mixer	MA-60 (code 02277)
120 W amplifier-mixer	MA-120 (code 02278)

FEATURES	MA-30	MA-60	MA-120
Type	Mixer amplifier with tuner/MP3/USB/SD/BLUETOOTH		
Power supply	AC 220V - 50/60 Hz		
Output power	30 W RMS	60 W RMS	120 W RMS
SPEAKER outputs	4 - 8 - 16 Ω / 70V - 100V		
Frequency band	60 Hz - 15 000 Hz (± 3 dB)		
Total harmonic distortion	< 0,5 %		
Signal-to-noise ratio	MIC : > 65 dB AUX/LINE : > 70 dB		
Tone Settings	Bass : + 10dB à 100 Hz Treble : + 10 dB à 10 000 Hz		
Cooling	Fan		
Consumption	60 W	100 W	200 W
Phantom power	+ 24 V switchable		
Protection	Thermal, overload and short-circuit protection		
Other	LINE Out		
Dimensions (W x D x H)	300 x 275 x 88		
Weight	3 kg	6,7 kg	7,8kg