

NEW

COMPACT MULTIMEDIA AMPLIFIER LA-240AMP

240W

8 Ω

BLUETOOTH



DESCRIPTION

This stereo mixer amplifier is available in 240W.

It operates in standard low impedance (8 Ω).
Power supply: AC 220–240V / 50–60Hz

Suitable for installations such as restaurants, shops, and retail outlets

FEATURES

Equipped with :

- 1 MIC input – Jack 6.35 mm
- 1 AUX input – Jack 3.5 mm (front panel)
- 2 AUX RCA inputs
- 1 PRE OUT output – RCA
- 2 speaker outputs (left / right) via screw terminals
- Independent volume control for each input
- Integrated multimedia player: TUNER / USB / Bluetooth with remote control
- Thermal, overload, and short-circuit protection

MODEL DESIGNATION

Stereo Amplifier 240W. LA-240AMP
(code 02804)

SPECIFICATIONS

	LA-240AMP
Type	Stereo mixer amplifier
Power Supply	AC 220-240V - 50-60Hz
Output Power	240 W
Speaker Outputs	8 Ω
Frequency Response	20Hz - 20 000 Hz (± 3 dB)
Total Harmonic Distortion	< 0.5%
Signal-to-Noise Ratio	> 80 dB
Cooling	Fan
Power Consumption	150W
Protections	Thermal, overload, and short-circuit
Dimensions (W x D x H)	330 x 260 x 66 mm
Weight	6 kg